

6 head HiFi VCR

HiFi Stereo

- Turbo Drive with Tape Position Indicator
- Digital Studio Picture Control
- Plug & Play
- Turbo Timer with Net Name Detection
- Record Link
- NexTView Link
- Smart Picture
- Front A/V

Platinum



MATCH  **LINE**

Let's make things better.



PHILIPS

6 head HiFi VCR



Product information

Reception - Installation

- Tuner: Hyperband, UHF, VHF
- Tuning - presets: PLL, CH entry, 99 presets
- TV Related Functions: 16:9 (pin 8), Analogue Direct Record, Analogue Follow TV, Next TV View Link (Rel 1.3)
- Time/Date Download: PDC (Time/Date), Text (Time)

User Interface

- Record Speed: Long Play, Standard Play
- Record Speed Selection: Auto LP, Per Menu
- Picture Improvement System: Digital Studio Picture Control, SMART Picture
- Audio Recording Level: Automatic
- Special Features: Auto Standby On/Off, Child Lock, Display On/Off, Illuminated Keys on Front

On Tape Standard

- Additional Playback Standard: BLACK & WHITE, NTSC Playback on PAL TV

Remote Control Unit

- Remote Control - Type Number: RT114/111
- Remote Control - Codes: VCR1, VCR2, TV-Multicode

Connectors Rear

- EXT1: Black, Euro CVBS in/out
- EXT2: Black, Euro Decoder, RGB loop through
- Rear Audio Connector: Cinch Stereo Out
- Terrestrial Antenna In/Out: 75 Ohms (IEC type)
- Mains Connector: Standard (IEC type)

Connectors Front

- Front A/V Connectors: Cinch CVBS In, Cinch Stereo in

Tape Deck

- Number of Video / FM Audio / Flying Erase Heads: 4 / 2 / 0
- Play: +1, -1, Repeat
- Additional Playback Features: Perfect Still, Multiple Search Speed, Multiple Slow Motion Speed
- Index Related Functions: Blank Tape Search, Next/Prev. index search
- Head Cleaning Mode: Automatic
- Tape Length Recognition: Automatic
- Tape Counter: Linear Relative (h.m.s.), Time Left (h.m.), Tape Position Indicator
- Winding / Rewinding Time (E180): 100 sec.
- Automatic Functions at Tape End: Rewind after Play, Eject after Record

Programming

- Number of Events: 6/month
- Record Control & Transmitter Identification: Net-name detection PDC, VPS
- Special Timer Programming: Turbo Timer
- Record Link: SCART 2

General

- Voltage: 198-264 V
- Frequency: 50Hz
- Backup Presets: 1yr
- Backup Clock - Calendar - Timer Event: 3hrs
- Power Consumption Play / Std-By / Low Power Std-By in W: 16 / 4.4 / <4
- Set Size - W x D x H in mm: 435 x 260 x 93
- Packaging - W x D x H in mm: 553 x 382 x 180
- Weight Including / Excluding package in kg: 5.5 / 3.6
- Equipment Supplied: Antenna, mains cord Euro

Product Highlights

• Digital Studio Picture Control

Digital Studio Picture Control keeps checking the quality of your videotapes and reproduces the best possible picture performance. Philips' Digital Studio Picture Control optimises the playback quality. It measures the characteristics of the tape, adapts the resolution and reduces the picture noise.

• Turbo Timer with Net Name Detection

Is Timer Programming complicated? No!
Is Timer Programming time consuming? No!
Just press the Turbo Timer button on the remote control, select the TV channel you want to record (directly by its name), set the start and the end time. That's it. All it takes is only a few seconds.

• Record Link

Your satellite receiver is equipped with a Timer function? Connect both your VCR and the satellite receiver with a SCART cable and make use of the „Record Link“ function. You just have to activate it and switch your VCR to std-by. As soon as the satellite receiver gets active, the VCR switches on and is set in the record mode. At the end of the recording it returns automatically to Stand-by.

• SMART Picture

With SMART picture, you can adapt the picture to your own preference: you can exaggerate the contours or suppress the noise from a rental tape. We offer you the possibility to play your tapes the way you like to see them.

	VR870L/58	VR870L/39	VR870L/16	VR870L/07	VR870L/02
Tuning/Install Features	Auto Search, Manual Store, Plug & Play, Welcome Screen	Auto Tuning, Manual Store, Plug & Play, Welcome Screen	Auto Tuning, Manual Store, Plug & Play, Welcome Screen	Auto Install, Manual Store, Plug & Play, Welcome Screen	Auto Tuning, Manual Store, Plug & Play, Welcome Screen
TV Systems Off Air	PAL B/G PAL D/K SECAM B/G SECAM D/K	PAL B/G PAL I SECAM B/G SECAM L/L'	PAL B/G	PAL I	PAL B/G
Sound Systems	German Stereo, Mono, NICAM	German Stereo, Mono, NICAM	German Stereo, Mono, NICAM	German Stereo, Mono, NICAM	German Stereo, Mono
Modulator	Pal GK (switchable)	Splitter	Pal G	Pal I	Pal G
Modulator Features	Electr. On/Off switch, Manual Frequency Adjustment	—	Electr. On/Off switch, Manual Frequency Adjustment	Auto Seek, Electr. On/Off switch, Manual Frequency Adjustment	Electr. On/Off switch, Manual Frequency Adjustment
Frequency Adj. Range	Ch 21 - Ch 55	—	Ch 21 - Ch 55	Ch 21 - Ch 55	Ch 21 - Ch 55
Preadj. modulation frequency	591.25 MHz (Ch 36)	—	591.25 MHz (Ch 36)	583.25 MHz (Ch 35)	591.25 MHz (Ch 36)
OSD Menu Languages	Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portuguese, Russian Cyrillic, Slovak, Spanish, Swedish	Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portuguese, Russian Cyrillic, Slovak, Spanish, Swedish	Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portuguese, Russian Cyrillic, Slovak, Spanish, Swedish	English	Czech, Danish, Dutch, English, Finnish, French, German, Hungarian, Italian, Norwegian, Polish, Portuguese, Russian Cyrillic, Slovak, Spanish, Swedish
Record / Playback Standard	MESECAM, PAL	MESECAM, PAL, SECAM	PAL	PAL	PAL
Programming System	Showview Daily/Weekly, Programming by Net-Name	Showview Daily/Weekly, Programming by Net-Name	Showview Daily/Weekly, Programming by Net-Name	Video Plus +, Daily/Weekly, Programming by Net-Name	Showview Daily/Weekly, Programming by Net-Name

Subject to modification without notice

Show View and Video+ are registered Trademarks of Gemstar Development Cooperation.

Let's make things better.



PHILIPS